

Wired ADSL2+ Modem Router

DL4201









Features:

- >2 in 1: Combine ADSL2/2+ Modem and Router in a single device
- >Provides Quick Start Wizard to help you set up your network in Minutes
- >Slim body design. Idea for home and office use
- >LEDs indicate port activity

Brief:

The netis DL4201 Wired ADSL2+ Modem Router is a high performance modem router that provides a full rate of ADSL2+ standard. It is a 2 in 1 device that combines the function of a high-speed DSL modem and a one-Port 10/100Mbps router. With the built-in Quick Start Wizard, you can easily create a secure and high-speed wired network to share files, music, photos, and printers with multiple computers.

www.netis-systems.com

Wired ADSL2+ Modem Router

DL4201

Specification:

Hardware 💎				
Interface LED	1 * 10/100M Auto MDI/MDIX RJ45 1 * RJ11 Internet ADSL LAN Power			
Power Supply	DC 5V/800mA(Output)			
Dimensions (L x W x H)	72x 69 x 25mm			
Software				
Standards	IEEE 802.3; IEEE 802.3u			
Data Rate	Downstream: Up to 24Mbps; Upstream: Up to 1Mbps			
ADSL Feature	Full-rate ANSI T1.413 Issue 2 ITU-T G.992.1(G.DMT); ITU-T G.992.2(G.Lite) ITU-T G.992.3; ITU-T G.992.5; ITU-T K.2.1			
ATM / PPP Protocols	ATM Forum UNI3.1/4.0 Bridged and routed Eth VC and LLC based mu PPP over ATM (RFC 2:	nernet encapsulation Itiplexing;	ATM Adaptation La	,
Main Features	DHCP, DHCP relay; VPN (PPTP, L2TP, IPS DNS Relay, DDNS; Virtual server, DMZ, A			7
Management	Web Based Configuration (HTTP), Remote management, Telnet management, command Line Interface, TR-069, SNMP, Web Based Firmware Upgrade, CWMP (TR-069), Diagnostic Tools			
Others Certification	CE, FCC			
Environment	Operating Temperature: 0°C~40°C Storage Temperature: -40°C~70°C Operating Humidity: 10%~90% non-condensing Storage Humidity: 5%~90% non-condens			
Package	1 * DL4201 1 * Ethernet Cable	1 * Quick Installat 2 * RJ11 cable	tion Guide	1 * Power Adapter 1 * Splitter

Topological Graph:

